		Custo	mer:				Mair	ntenance	schedule	•		
5	unKid	Seria	l no.:					Comfor	t Star	06-0	8	Daily
Ma	Sv	vitch off	^t the mair		- h before pe	erforming bserve th	mainte e opera	- nance we Perform	-B-C TI ork (except safe test ru maintenan formed	with test	quired!	Info Chap-
	Safety s	vstems		Functional c Check functi				stop buttons.			ter no. 06-04 06-04	
	Haul rop	-		{	Overrun afte Visual inspe No rope twis	er stop by a ction of the	safety de haul rop	evice e.				06-04 06-05 06-05
C					Check rope Check topog	height graphy (load	ding and	unloading	area, route)			03-02 03-01
					Remove sno No foreign o Check cover	bjects in th	e area of	^t the syster		return.		03-01 03-02 06-04
C		e system eturn stat				for damag	e, comple	eteness an	d dirt. Repla	ce or clean	if ne-	03-28 03-28
				F	Check for qu	iet running / ction (posit	bearing i ion/faster	noise from	the drive and be rollers, rop			
 	Jan	Feb	Mar	Apr	May	Jun	Jul	Aug	Sept	Oct	Nov	Dec
1	Jan	1.00	ivial		iviay	Juil	Jui	Aug		001		
2 3					+							
4												
5 6												
7												
8 9												
10												
11 12				ļ								1
13												
14												
14 15 16												
14 15 16 17												
14 15 16 17 18 19												
14 15 16 17 18 19 20												
14 15 16 17 18 19												
14 15 16 17 18 19 20 21 22 23												
14 15 16 17 18 19 20 21 22 23 24												
14 15 16 17 18 19 20 21 22 23 24 25												
14 15 16 17 18 19 20 21 22 23 24												
14 15 16 17 18 19 20 21 22 23 24 25 26 27 28												
14 15 16 17 18 19 20 21 22 23 24 25 26 27												

SunKid	Customer:		Maintenance schedule		weekly		
Junited	Serial no.:		Comfort Star	06-09	weekiy		
Swit	ch off the main s	switch before performing ma Observe the c	intenance work (exce Perform safe test peration and mainter	runs as requ	uired!		
<u>Maintenanc</u>	e object	Task to be performed					
Allgemein		Perform daily maintenanc	e work!		no.		
		Check the haul rope for d			06-05		
Haul rope		Check for quiet running.			06-05		
		Check for loose screws			06-02		
Complete Syster	m	Check for quiet running, t		points	06-05		
		Particularly thorough clea Check tensioning device	ring of snow and ice		06-04 06-06		
Drive station - R	eturn station	Check position of the ice	scraper		06-05		
Eor maintonanc	so timo documenta	tion of the maintenance persor			00.00		
Calendar week							
1		28					
1 2		29					
1							
1 2 3 4 5		29 30 31 32					
1 2 3 4 5 6		29 30 31 32 33					
1 2 3 4 5 6 7		29 30 31 32 32 33 34					
1 2 3 4 5 6 7 8		29 30 31 32 33					
1 2 3 4 5 6 7 8 9		29 30 31 32 32 33 34 34 35					
1 2 3 4 5 6 7 8 9 10 11		29 30 31 32 32 33 34 35 36 36 37 37 38					
1 2 3 4 5 6 7 8 9 10 11 12		29 30 31 32 32 32 32 32 32 32 32 32 32 32 32 32					
1 2 2 3 3 4 5 6 7 8 9 10 11 12 13		29 30 31 32 32 33 34 35 36 36 37 37 38 39 40					
1 2 3 4 5 6 7 8 9 10 11 12 13 14		29 30 31 32 32 32 32 32 32 32 32 32 32 32 32 32					
1 2 2 3 3 4 5 6 7 8 9 10 11 12 13 14 15 16		29 30 31 32 32 32 32 32 32 32 32 32 32					
1 2 2 3 3 4 5 6 7 8 9 10 10 11 12 13 13 14 15 16 17		29 30 31 32 32 33 34 35 36 36 37 37 38 39 40 40 41 42 43 44					
1 2 3 4 5 6 6 7 8 9 10 11 12 13 13 14 15 16 17 18		29 30 31 32 32 33 34 35 36 37 36 37 38 36 40 41 42 43 44 45					
1 2 3 4 5 6 6 7 8 9 10 11 11 11 12 13 13 14 15 16 17 18 19 19		29 30 31 32 32 32 32 32 32 32 32 32 32					
1 2 3 4 5 6 7 8 9 10 11 11 12 13 13 14 15 16 17 18 19 20		29 30 31 32 32 32 32 32 32 32 32 32 32					
1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 20 21		29 30 31 32 32 32 32 32 32 32 32 32 32					
1 2 3 4 5 6 7 8 9 10 10 11 12 13 13 14 15 16 17 18 19 20 21 22		29 30 31 32 32 32 32 32 32 32 32 32 32					
1 2 3 4 5 6 6 7 8 9 10 11 11 11 12 13 14 15 16 17 18 19 20 21 22 23		29 30 31 32 32 32 32 32 32 32 32 32 32					
1 2 3 4 5 6 7 8		29 30 31 32 32 32 32 32 32 32 32 32 32					

Sunkid	Customer		Maintenance schedule				
Junita	Serial-No.:		Comfort Star	06-10	Monthly		
Switch off the main switch before performing maintenance work (except with test runs). Perform safe test runs as required! Observe the operation and maintenance instructions!							
<u>Maintenance c</u>	<u>bject</u>	Tas	k to be performed		Info Chapter no.		
General		Perform daily and weekly	maintenance work!				
		Check the pulley rubber for lubricants	Check the pulley rubber for wear – rubber surface must be clear of lubricants				
		Check gears for oil leakag	Check gears for oil leakage				
Drive - return station			Gear unit - maintenance in accordance with manufacturer's instructions - replace gearbox oil after the first 500 operating hours. Then maintenance per P.06-06.				
		Grease bearing unit of the hub).	Grease bearing unit of the drive unit and return hub (grease nipple on hub).				
		Check belt drive (transmis	Check belt drive (transmission).				
		Check rope rollers for wea (no flat / worn areas).	Check rope rollers for wear and freedom of movement* (no flat / worn areas).				
Height adjustment		Check the height adjustme	06-07				

	Jan	Feb	Mar	Apr	May	Jun	Jul	Aug	Sept	Oct	Nov	Dec
Date:												
Name:												

Comment:

*	Customer:		Maintenance schedule		Annu-			
Sunkid	Serial no.:		Comfort Star	06-11	ally			
	8	ah hoforo porforming m						
Switch off the main switch before performing maintenance work (except with test runs). Perform safe test runs as required!								
		Observe the	operation and maintenance	instructions				
Maintenanc	e object	Tas	sk to be performed		Info Chapter no.			
General			monthly maintenance work!		110.			
Drive motor and	d gearbox	operating hours or 5 year		ns - after 4000	06-06			
Rollers and bea	arings	Check rollers for ease of Lubricate bearing bolts via	a grease (at beginning / end of	season)	06-06 06-06			
	•	Bearings must be free of	olay and noiseless		06-03			
Haul rope		10 years. Otherwise, obs	sed, the haul rope must be repla erve the maintenance intervals s ce instructions of the manufacture	pecified in the				
Electrical eleme	anto	Check overcurrent, overv Check fans of frequency of	oltage, earthing and lightning pro	otection				
Electrical eleme		Check plugs, cables and						
		sidence, etc.).	other wear, formation of rust, tear	rs, ground sub-				
		Check foundations Check screws for firm sea	ting and tighten if necessary		 06-02			
		Grease guides and screw	s and keep clear of corrosion					
		Visual inspection of the gr (e.g. plant manager).	ip hoist by a competent and train	ned person	06-06			
		Grease force gauge and l			06-06			
		Winch ropes must be rep		mnonents must				
Complete syste	m	The following safety-relevant electrical and mechanical components must be replaced after no more than 20 years (after 1st commissioning).						
		Mechanical components:						
		Latching lock (main carria Bearing bolt drive/return u						
		Drive shaft (check / inspect for cracks)						
		Return hub (axle - inspect for cracks) V-belt and V-belt pulleys						
		Electrical components:						
		Control and safety devices,						
		Cables and plugs must be checked and replaced if necessary						
Test run		Check the functions of the	e system during a test run.					
<u>Comment:</u>								
Date	Technician	Tester	Stamp					
				BAL-CS25-GB-0	6 R01 pub			